

PRVPATENT- OCH REGISTRERINGSVERKET
Patentavdelningen

REC'D 04 MAY 2004

WIPO

PCT

**Intyg
Certificate**

Härmed intygas att bifogade kopior överensstämmer med de handlingar som ursprungligen ingivits till Patent- och registreringsverket i nedannämnda ansökan.

This is to certify that the annexed is a true copy of the documents as originally filed with the Patent- and Registration Office in connection with the following patent application.



(71) Sökande Linnman Elektronik AB, Åkersberga SE
Applicant (s)

(21) Patentansökningsnummer 0301131-9
Patent application number

(86) Ingivningsdatum 2003-04-14
Date of filing

Stockholm, 2004-04-20

För Patent- och registreringsverket
For the Patent- and Registration Office

Marita Öun

Avgift
Fee

**PRIORITY
DOCUMENT**
SUBMITTED OR TRANSMITTED IN
COMPLIANCE WITH RULE 17.1(a) OR (b)

BEST AVAILABLE COPY

COMMON FIELD BUS FOR DATA AND ENERGY TRANSFER

Ink. t. Patent- och reg.

TECHNICAL FIELD

2003-04-1

Huvudfaxen Kas

5 The present invention relates in general to distribution of control signals and electrical power in an electrical system, and in particular to distribution of control signals between a central unit and a number of nodes over the conductor that powers the nodes.

10

BACKGROUND

15

Today, there are several data buses or field buses that are intended to distribute control signals between a central unit, also called a "master", and several nodes, also called "slaves". A number of these field buses make use of only one conductor pair to distribute both control signals, in the shape of data pulses, and electrical energy, for operating the nodes and their peripheral units. One typical example is presented in the US patent 4,139,737. Here, a pulse train of square pulses is superimposed on a supply voltage.

20

25

30

35

40

45

50

55

60

65

70

In prior art field buses that transfers data and energy on the same conductor pair, different pulse trains are sent over the bus to transfer data. This data is interpreted as addresses to different nodes, as identities of different information packages, as instructions or control signals or as measurement values or status information from nodes. In most prior art pulse trains, each pulse or each time slot is used to transfer one data bit, i.e. the information is normally in a binary form. During the pulse or time slot, the voltage or current on the bus is either high or low, representing either a data bit with the value 1 or 0, respectively. Alternatively, pulses having different duration can represent different digital values.

The US patent 4,477,896 is another typical example of a system utilising transmission of data and power over the same conductor pair. Information

from a base unit to nodes is sent as time divided voltage pulses. Information from nodes to the base unit is instead represented as time divided multiplexed current pulses. The voltage signals are preferably superimposed on a DC potential, which is used as a power source for the nodes.

5

Prior art systems of this kind are favourable in many respects, e.g. since they reduce the need for multiple parallel control signal wiring. However, a number of disadvantages still remains. A first problem is that the pulse duration occupies a relative large portion of the total time. During the pulses, the ability of the bus to transfer energy, i.e. the efficiency in powering of the nodes, is detrimentally affected. The powering arrangement therefore has to be deliberately overdimensioned to compensate for this lower efficiency.

10

15

A second problem is connected with the use of such field buses in environments that are sensitive for electromagnetic radiation. The use of frequently occurring substantially square-shaped pulses gives rise to relatively large amounts of electromagnetic radiation. Depending on the used pulse frequency, the radiated energy appears in different frequency ranges. Since the square pulses furthermore involves a relative large portion of high-frequency overtones, radio frequency disturbances are to be expected in many cases. In environments sensitive to such disturbances, the emission of electromagnetic energy from the data bus may cause large problems.

20

25

30

The digital data is in prior art systems typically transmitted as relative long sequences of pulses, where the voltage value at a certain time has a certain meaning. The emission of the pulses is typically controlled by a clock device in the sending unit. The interpretation in the receiving end is analogously strongly dependent on that the receiving unit has basically the same definition of time. The receiving unit thus has to have a clock device with a stability that is accurate enough to ensure a correct interpretation of the pulses during the entire pulse sequence. However, accurate clock devices are

relatively expensive and this causes a problem when very simple and inexpensive nodes are to be connected.

5 A typical communication between the central unit and the remote nodes takes place at the command of the central unit. In a typical signalling procedure, the central unit first sends out an address to a node to be contacted. Then, an amount of data may be sent from the central unit to the addressed node. The node may then respond, e.g. by a confirmation. Only
10 the addressed node has this possibility, since there cannot exist any simultaneous signalling from more than one node at a time. The nodes have in a typical case no or at least small possibilities to initiate a communication with the central unit at its own initiative. This may cause problems when emergency situations occur. If an emergency situation occurs at a node, the node has to wait for the central unit to address it, before any message of the
15 emergency situation can be transferred. If the central unit serves a large number of nodes, it may take a long time between each successive addressing.

SUMMARY

20 An object of the present invention is to provide methods and devices for signalling and powering on a common bus having a higher power transferring capability during data transfer. Another object of the present invention is to provide such methods and devices presenting a reduced
25 emission of electromagnetic radiation. Yet another object of the present invention is to provide such methods and devices that are operable with reduced demands of clock stability. It is also an object of the present invention to provide such methods and devices enabling a fast transmission of express messages from any remote node.

30 The above objects are achieved by methods and devices according to the enclosed patent claims. In general, the present invention uses the time difference between two successive current or voltage pulses to represent

different data values. The time differences can assume more than two different predetermined values, and each pulse can thereby represent more than one data bit. This is a variation of a pulse position modulation. A central unit transfers data to remote nodes by modulating voltage pulses onto a base voltage, which also provides electrical power to the nodes. The time difference between successive voltage pulses represents a data value. Preferably, the nodes transfer data back to the central unit using current pulses, whereby the time difference between the latest voltage pulse and the current pulse represents the data sent to the central unit. Data from two or more nodes are allowed to be transferred simultaneously without disturbing each other. A time difference between two successive voltage pulses having a value within a predetermined regions of values, e.g. above a predetermined threshold value, can be used as indication of a frame start and/or end as well as a time reference calibration. Since only the time position of the pulse is of importance for the interpretation of the data content, almost any pulse shape can be used. Preferably, the pulses used for data transmission have a shape involving as small overtone content as possible. Preferred pulse shapes are based on triangular or sinusoidal shapes. The base voltage on the bus can be AC or DC.

Since data is transferred utilising a smaller number of pulses than in binary modulation and since the pulse shape preferably is selected to give rise to a small overtone contribution, the amount of electromagnetic radiation emitted from the bus is significantly reduced. The remaining emitted electromagnetic radiation is also of a more stochastic type, which will appear more as a random noise than interfering electromagnetic signals. Furthermore, the reduced number of pulses also increases the efficiency of the bus as a power distribution means. Due to time calibration routines that are easy to implement and are occurring relatively frequently, the demands for the stability of clock devices are reduced. This in turn permits simpler and more inexpensive clock devices to be used. The possibility to transfer data simultaneously from more than one node at a time without destroying the

data content of each other opens up for fast express messages to be sent in the bus system.

BRIEF DESCRIPTION OF THE DRAWINGS

5

The invention, together with further objects and advantages thereof, may best be understood by making reference to the following description taken together with the accompanying drawings, in which:

10

FIG. 1 is a block scheme of an embodiment of an electrical system according to the present invention;

FIG. 2 is a diagram illustrating voltage pulses according to an embodiment of the present invention;

FIG. 3 is a diagram illustrating voltage pulses according to another embodiment of the present invention;

15

FIG. 4 is a diagram illustrating voltage and current pulses according to an embodiment of the present invention;

FIG. 5 is a diagram illustrating voltage and current pulses according to another embodiment of the present invention;

20

FIG. 6 is a block diagram of an embodiment of a central unit according to the present invention operating with constant voltage supply;

FIG. 7 is a block diagram of an embodiment of a node according to the present invention operating with constant voltage supply;

FIG. 8 is a diagram illustrating voltage and current pulses according to an embodiment of the present invention based on alternating voltages;

25

FIG. 9 is a block diagram of an embodiment of a central unit according to the present invention operating with alternating voltage supply;

FIG. 10 is a block diagram of an embodiment of a node according to the present invention operating with alternating voltage supply;

30

FIG. 11 is a diagram illustrating voltage and current pulses according to an embodiment of the present invention allowing simultaneous transferring of more than one current pulse within one and the same main pulse period;

FIG. 12 is a schematic illustration of data frames transferred in an embodiment of an electrical system according to the present invention involving express messages; and

FIG. 13 is a flow diagram illustrating an embodiment of a method according to the present invention.

DETAILED DESCRIPTION

In the present invention, the bus used is characterised as a conductor pair, between which a certain voltage is provided. Current pulses are furthermore transferred on preferably one of the conductors. Anyone skilled in the art realises that also a single conductor combined with grounding of the different components will have a similar behaviour. In the expression "conductor pair" is therefore also included the case where one conductor is ground.

In Fig. 1, an electrical system 1 is schematically illustrated as a block diagram. The electrical system 1 comprises one central unit 10 and a number of remote nodes 20-24. The remote nodes 20-24 are connected to an electrical bus 30 comprising a pair of conductors 31, 32. The bus 30 is in turn connected to the central unit 10. Each node 20-24 is associated with at least one peripheral unit 40-44. The node 20-24 is thereby responsible for monitoring and/or controlling of the associated peripheral unit 40-44. For instance, node 20 controls the power to the peripheral unit 40 and node 21 senses the position of the switch 41. The central unit 10 is arranged to co-ordinate the operations of the different nodes 40-44, i.e. sending control messages to the node and/or receiving data concerning the nodes, e.g. status or any measured quantities.

The central unit comprises a voltage source 12 connected to apply a base voltage between the conductors 31, 32 of the bus 30. The nodes 20-24 and the peripheral units 40-44 have thereby a possibility to obtain necessary operation power from the bus 30.

5 The central unit 10 further comprises a voltage modulator 14. The voltage modulator 14 is arranged to modulate voltage pulses between the two conductors 31, 32. The time difference between successive ones of these voltage pulses represents data to be transferred from the central unit 10 to the nodes 20-24. The nodes 20-24 analogously comprise detectors 25 for identifying the modulated voltage pulses. The time difference between successive voltage pulses is determined and an interpreter 26 interprets the time difference as data. The detector 25 can of course comprise a detector that actually measures another quantity than voltage, but where simple relations known by anyone skilled in the art directly relate this quantity to voltage. For instance, current through a known load connected between the bus connectors could be used as an "indirect" voltage detector.

15 In a preferred embodiment, the nodes 20-24 are also allowed to transfer data back to the central unit 10. The nodes 20-24 therefore comprise current pulse means 27, which are arranged to enable introduction of current pulses on the conductors 31, 32. The time difference between the closest previous voltage pulse from the central unit and these current pulses represents data to be transferred from the remote nodes 20-24 to the central unit 10. Analogously, the central unit 10 comprises a current detector 16, means 17 for determining the time difference between the closest previous voltage pulse created by the central unit 10 and these current pulses and associating means 18, interpreting the time differences as data.

25
30 As mentioned above, communication according to the present invention uses a varying time difference between two successive pulses to transfer data from the central unit to the nodes. The time distance can assume more than two discrete or distinct pre-determined values. This is in other words a modulation based on pulse position differences. By combining this type of pulse position modulation for data transfer with a simultaneous transfer of electrical energy, large advantages can be achieved compared with prior art arrangements. Large amounts of data can be transferred without reducing

the ability of the bus to supply electrical energy to the nodes and peripheral units. Furthermore, the emitted electromagnetic energy is reduced, which reduces electromagnetic disturbances caused by the data transfer.

5 A first embodiment of a communication scheme is described in connection with the diagram of Fig. 2. Here, a voltage signal U_b is provided between the conductors of the communication and powering bus. The base voltage used for powering purposes is in this embodiment a DC voltage of a nominal value of U_0 . In Fig. 2, the time variation of the voltage signal in a time interval is
10 illustrated by the curve 101. In the present embodiment, data is transferred in frames or pulse trains on the bus between the central unit and the nodes. The curve 101 presents two complete frames lasting for 47 and 53 time units, respectively. In the present embodiment, the time unit used is 1 ms, whereby the frames last $\Delta T_1=47$ ms and $\Delta T_2=53$ ms, respectively. The total
15 frame duration is in this embodiment evidently not constant.

The central unit provides a number of main voltage pulses 102 on the bus. During the main pulses 102, the voltage on the bus is in this embodiment lower than during the remaining time of the frame. The time distance
20 between the falling pulse edges of the main pulses 102, hereinafter called main pulse period, represents one data unit of more than one binary bit. In the present embodiment, the first frame comprises 4 main pulse periods Δt_1 - Δt_4 . The first three periods Δt_1 - Δt_3 corresponds to one data unit each. In this
25 embodiment, the main pulse periods may vary between 4 ms and 19 ms, in steps of 1 ms, which means that 16 different values are available. One data unit thus represents 4 binary bits ($2^4=16$). The first main pulse period Δt_1 is 7 ms long, which corresponds to a number "3". The second main pulse period Δt_2 is 5 ms long, which corresponds to a number "1" and the third
30 main pulse period Δt_3 is 15 ms long, which corresponds to a number "11".

The frames are terminated by a relatively long main pulse period Δt_4 , which exceeds the duration of any other main pulse period containing ordinary data. This long main pulse period Δt_4 is a calibration pulse period and is in

this embodiment added in the end of each frame. The duration of the calibration pulse period is in this case always 20 ms. The main pulse period Δt_5 is thus also 20 ms. The characteristic feature of a calibration pulse period is in this embodiment that it exceeds a predetermined duration, in this embodiment 19.5 ms.

In other embodiments of the present invention, the calibration pulse period can be characterised in other ways, e.g. being shorter than a predetermined duration or having a duration within a predetermined range of durations.

The calibration pulse period may be used for several purposes. The first purpose is to label the end of the frame. Any receiving device can then treat any successive pulses as belonging to a new frame. The voltage pulse ending the calibration pulse period therefore also serves as a synchronising pulse. In this embodiment, the subsequent frame starts with this ending voltage pulse of the calibration pulse period. In a general case, depending on the actual communication procedure used, a new frame starts with the m :th voltage pulse following a calibration pulse period. In this embodiment $m=1$. By doing this, frames with varying number of data units can be used. For instance, the frame corresponding to ΔT_2 has four data units.

The calibration pulse period can also, as the name indicates, be used for calibration purposes. In the embodiment of Fig. 2, the calibration pulse period has always the same duration. This enables any node to measure the time of this period and adjust its time references in such a way that this measured time corresponds to the nominal one. In this way the node time reference is adjusted to the central unit time reference. If the calibration pulse period is transmitted fairly frequently, perhaps tenth of times every second, the demands of the stability of the node time measuring means may be mitigated. The time measuring means may be allowed to vary over longer times or over different surrounding temperatures. The oscillators controlling the time measurement in the nodes are not needed to be built on expensive crystal or ceramic resonators. Instead, inexpensive RC oscillators can be

used, without high demands on component stability. Often, an oscillator having frequency controlling components integrated directly with other components in an integrated circuit may be used. This gives a significant cost reduction in comparison with prior art.

5

In other embodiments, the calibration period does not have to be included in every frame. It may e.g. be decided that calibration periods only are sent every 10th or 100th frame. This saves some data transmitting capacity to be used for useful data units instead. This is easily implemented in embodiments where each frame has a predetermined number of data units. However, by starting each frame with a data unit specifying the actual number of total data units following in the present frames, also varying frame length systems can use occasionally occurring calibration periods.

10

The energy transfer can be provided by constant voltages or by means of alternating voltages. Every disruption or pulse of this voltage means that the energy transfer capability is reduced. It also means that the electromagnetic disturbances emitted from the bus increases. Both these disadvantages are minimised by devices and methods according to the present invention, since the number of voltage disruptions or pulses can be reduced significantly. The reason for this is that each pulse can carry information of significantly more than one binary bit, which is more than in normal binary modulation systems.

20

The fact that the pulses on the bus are situated at different time distances implies by itself an advantage. Any electromagnetic disturbances from the pulses of the bus then assume characteristics of more or less stochastic noise instead of continuous disturbance frequencies.

25

The content of the frame can be formatted according to different schemes. One possibility is to let the first data unit define an address of a node to which the remaining data units are intended for. The addressed node can detect the address and then assimilate the following data. Nodes that are not

30

addressed can remain listening to the voltage pulses, but not extracting the data contained therein. Anyone skilled in the art understands that there might be many different possible variations of the actual format of the data communication.

5

10

15

Fig. 3 illustrates a curve 103 of voltage pulses according to another embodiment of the present invention. In this embodiment, each frame has a constant duration. ΔT_3 and ΔT_4 are in this case both 54 ms long. The calibration periods Δt_6 and Δt_7 are instead of varying duration. The identification of Δt_6 and Δt_7 as calibration periods are, however, still possible since the duration exceeds the predetermined threshold of 19.5 ms. Synchronisation can then also be performed. Any calibration of node time references is in the present embodiment performed using the entire length of the frame, not the actual duration of the calibration period. The calibration period thus serves the main purpose of filling up the frame length to the predetermined duration.

20

25

30

The voltage pulses 102 described above are used for transferring data from the central unit to different nodes. The central unit therefore generates the voltage pulses 102 on the bus. Fig. 4 illustrates diagrams of curves of voltage 109 and current 110 in the bus during a main voltage pulse 102 generated by the central unit. In this embodiment, the voltage pulse 102 has a triangular shape. The voltage pulse 102 starts at time t_0 , having the value of U_0 . The voltage is reduced linearly and passes the voltage U_1 at time t_1 . After a minimum at U_2 , the voltage is again raised linearly and the pulse ends at t_2 . Preferably, the first crossing of U_1 , i.e. at the falling edge, is used as defining the position of the pulse. The triangular shape of the pulse has certain advantages compared with square pulses, since square pulses give rise to larger amounts of high-frequency overtones in the emitted electromagnetic spectrum. Even more rounded-off pulse shapes would give even better radiation behaviour, but will at the same time increase the complexity of the pulse forming devices.

When the central unit decreases the voltage of the bus, also the current flowing in the bus will decrease, as indicated by the current curve 110, i.e. a current pulse 104 is also created. If dominantly resistive loads are present, the current pulse 104 will have basically the same shape and timing as the voltage pulse 102. An average current, before the pulse 104, I_0 , is reduced to I_2 at the minimum voltage U_2 , passing I_1 at the pulse position t_1 .

Up to now, only transferring of data from the central unit to the nodes has been discussed. However, the present invention also allows for "upbus" data communication, i.e. transferring of data from the nodes to the central unit. According to a preferred embodiment of the present invention, data is transferred from the nodes to the central unit by using current pulses. A node is according to the present invention allowed to during a short time increase or decrease the load on the bus. Such a fast change of the bus load will give rise to a positive or negative current pulse, respectively, on the bus. The main voltage pulse generated by the central unit may still be used as a time reference, and a time difference between the main voltage pulse and the generated current pulse may represent a certain data value in analogy with earlier discussions.

Fig. 4 illustrates voltage and current curves 109, 110 caused by an explanatory embodiment. A main pulse distance H between two successive main voltage pulses 102 has been divided into three parts, H_s , H_n and H_c . (The main pulse distance H corresponds to the periods ΔT_1 to ΔT_4 in Figs. 2 and 3.) During H_c , one may expect data from the central unit, i.e. next main voltage pulse 102. The minimum duration of a main voltage period is thus t_c , according to earlier discussions. (In Figs. 2 and 3, t_c was equal to 4 ms.) The part H_s is used by the nodes to change the current that is supplied to the peripheral units of the nodes. The damped oscillation behaviour 105 of the current curve 110 illustrates the result of such a change of the bus load and is believed to be negligible at time t_n . By not allowing for any significant changes of the bus load during the period H_n , i.e. between t_n and t_c , the

current from the bus generator will during this period be substantially constant.

5 According to an embodiment of the present invention, the node that is last addressed is allowed to change its load towards the bus during the period H_n . This will give rise to a current pulse 106 on the bus. In Fig. 4, the load is increased, starting at time t_3 , and ending at t_5 . A position of the generated current pulse 106 can be defined as t_4 . The node controls the position in time of the current pulse 106. The current pulse 106 should be situated within the period H_n , have a specific time distance Δt_s from the main voltage pulse 102 and represent the data value to be transferred.

10 Other embodiments may have the addressing of a node in a determined previous frame, i.e. the addressed node has a certain time available before the answer is sent.

15 The time distance Δt_s is as mentioned above a function of the data that the node is to be sending. The minimum duration of Δt_s is t_n . If the node for instance wants to send data corresponding a value of 1, the current pulse is created at $t_n + 1 \cdot 10 \mu s$. (In this example, each discrete current pulse position is separated by $10 \mu s$.) If the value is intended to be 7, the current pulse is instead created at $t_n + 7 \cdot 10 \mu s$.

20 The central unit senses when the above described fast changes of the bus current passes a predetermined value, i.e. the moment t_4 . It also measures the time elapsed between the time t_1 of the main voltage pulse starting the main period and the time t_4 . This time is interpreted in the central unit as a corresponding data value.

25 Fig. 5 illustrates the voltage and current curves 111, 112 of pulses created by another embodiment of the present invention. In this embodiment, the node decreases its load towards the bus, whereby negative current pulses 106 instead are created.

Analogously, the voltage pulses created by the central unit can in alternative embodiments be positive.

5 Fig. 6 illustrates a block scheme of an embodiment of a central unit 10 according to the present invention. The central unit 10 comprises a voltage source 12, in this embodiment a battery, which supplies power to the operation of the central unit itself as well as to the bus for further transfer to the nodes. The most essential part of the central unit 10 is a microcontroller 10 19. The microcontroller 19 is powered from the voltage source 12. An output control signal means 67 in the microcontroller 19 is arranged to provide a signal to a transistor 65. The transistor 65 becomes conducting by the signal and connects the voltage of the battery 12 over bus terminals 33 and 34. The voltage modulator 14 comprises in this embodiment the transistor 65 and 15 the output control signal means 67 of the microcontroller 19.

The current that is provided out on the bus passes a shunt resistor R1. By connecting input terminals 68, 69 of a voltage detecting means 66 in the microcontroller 19 to points on each side of the shunt resistor R1, a voltage 20 drop over the shunt resistor R1 can be measured, which is proportional to the current on the bus. The current detector 16 comprises in this embodiment the shunt resistor R1 and the voltage detecting means 66 of the microcontroller 19. In this embodiment, the microcontroller 19 further comprises the means 17 for detecting the time difference associated with the 25 detected current pulses as well as the associating means 18, interpreting the time differences as data.

Fig. 7 illustrates a block scheme of an embodiment of a node 28 according to the present invention. The details of the node design are dependent also on the type of peripheral unit that is connected. In order to describe some different alternatives, the model node 28 of Fig. 7 is provided with three 30 peripheral units; a peripheral unit 45 demanding constant voltage supply at all instances, a peripheral unit 46 demanding voltage supply, but with less

stability requirements and a peripheral unit 47 not demanding any supply of voltage.

5 The main part of the node 28 is constituted by a microcontroller 29. Current from a capacitance C1 is supplied to the microcontroller 29. The capacitance C1 is charged from the bus via a diode D1. This charging current necessary to drive the microcontroller 29 is negligible in comparison to other currents extracted from the bus.

10 An input 73 of a voltage detecting means 25 in the microcontroller 29 is connected to the bus by bus terminals 58, 59 in order to sense the modulated voltage pulses and determine the time differences there between. The voltage detecting means 25 is in turn connected to an interpreter means 26, also implemented in the microcontroller 29 in this embodiment. These
15 microcontroller part means are thus responsible for detecting data sent from the central unit.

An output control signal means 78 in the microcontroller 29 is arranged to provide a signal to a transistor 70 via an output 74. The transistor 70
20 becomes conducting by the signal and loads the bus with a current. The output control signal means 78 can control the transistor 70 to extract different currents from the bus. The current pulse means 27 comprises in this embodiment the transistor 70 and the output control signal means 78 of the microcontroller 29.

25 A transistor 71 is controlled by the microcontroller 29 via an output 75. This transistor 71 is used to provide energy to the peripheral unit 45. When the transistor 71 is made conducting, full voltage is provided to the peripheral unit 45 even during periods when the bus voltage is low, due to the use of the diode D1 and capacitance C1. This corresponds to a more traditional way to provide voltage to peripheral units. The size of the capacitance C1 should be selected in proportion to the energy amount that should be transferred during the periods when the bus voltage is low.

A transistor 72 is controlled by the microcontroller 29 via an output 76. This transistor 72 is used to provide energy to the peripheral unit 46. In this case, the energy is provided to the peripheral unit 46 essentially directly from the bus, just passing the transistor 72. An advantage with such a powering principle is that no energy is lost due to any passage of a diode. If the peripheral unit 46 can accept the short periods of low voltages on the bus caused by the data transfer, this solution is more power efficient. If only such peripheral units are connected to the node, the demands on the capacitance C1 are entirely determined by the microcontroller 29 demands, since the capacitance C1 provides energy only to the microcontroller 29. The power consumption of the microcontroller is typically very small compared to the power consumption of typical peripheral unit, which means that the capacitance C1 can be much smaller and more inexpensive.

The node 28 can also be connected to a peripheral unit 47, which in this embodiment is a switch. This is connected to the microcontroller 29 via an input 77.

The base voltage on the bus, responsible for the power supply of the node and their peripheral units, may also be alternating. Some minor modifications of the principles for the DC case described above have to be performed. However, the basic principles are the same.

Fig. 8 illustrates curves 113, 114 of the voltage on the bus U_b and the current I_c from the central unit, respectively, when the energy transferred between the central unit and the nodes is based on a substantially sinusoidal alternating voltage. In this case, a limitation is introduced, since the possibility to introduce voltage pulses on the is is limited during the time interval near the zero-crossing point of the alternating voltage. One embodiment avoiding such limitations is illustrated in Fig. 8. Here, two different types of main voltage pulses are present. A first type 60 occurs at the initial part of each half period of the alternating voltage. This first type

60 of main voltage pulse indicates the beginning of a main pulse period. A second type 61 indicates the end of the main pulse period. The maximum length of a main pulse period has in this embodiment to be less than the half period time of the alternating voltage. The time differences $\Delta t_9 - \Delta t_{12}$ represent the data units sent from the central unit out on the bus. As anyone skilled in the art realises, the data transfer rate will be somewhat lower in such a case.

As seen from Fig. 8, in the voltage curve U_b , every main pulse period is started by the central unit lowering the absolute value of the voltage for a short time in relation to the sinusoidal alternating voltage. This is done in the beginning of each half period of the sinusoidal alternating voltage. This means that the voltage pulse is a negative pulse during a half period of the alternating voltage presenting positive voltages, while the voltage pulse is a positive pulse during a half period of the alternating voltage presenting negative voltages. The central unit also terminates each main pulse period by again lowering the absolute value of the voltage for another short time. In the present example, the main pulses form a complete data frame. The last main pulse period Δt_{12} is a calibration period. In the present example, the first three main pulse periods have the lengths of 7, 3 and 8 ms respectively, while the calibration period in this embodiment is 9 ms long. The total frame ΔT_s is constant and 56 ms long, which corresponds to a frequency of the alternating voltage of 35.7 Hz.

The current curve 114 of Fig. 8 illustrates the current flowing from the central unit. At the moments when a main voltage pulse is created, the absolute value of the current is decreased compared with the substantially sinusoidal alternating current flowing from the central unit. This reduction, causing current pulses 62, 63 is directly caused by the corresponding reduction in voltage 60, 61. This is in analogy with the DC case.

The main voltage pulse 60, 61 or the corresponding current pulses 62, 63 are to be detected in the nodes. Since an alternating base voltage is used, no threshold value can be used to determine the existence of a pulse. Instead,

the derivative of the voltage or current can be used. The fast change of the voltage or current gives derivatives that differ significantly from the derivative of the base voltage and current, respectively.

5 An alternative approach is to compare the actual current or voltage with a calculated reference current or voltage. This reference current or voltage is provided to resemble the sinusoidal base voltage or current as good as possible.

10 Also in the alternating base voltage case, the nodes are allowed to send data back to the central unit. In Fig. 8, in each half period of the sinusoidal alternating current, there is also a short increase in absolute current, a current pulse 64, in relation to the sinusoidal alternating current. This increase is generated from one of the nodes on the bus and is according to
15 the present invention used for sending data from the nodes to the central unit. The data values are as in the previous embodiments related to the time difference between the voltage pulse 60 in the beginning of each main pulse period and the current pulse 64 generated by the node. In Fig. 8, these data are represented by the time differences Δt_{13} to Δt_{16} . In the present example,
20 these time differences assume the values of 1, 2, 2 and 1 ms, respectively. The current pulses 64 generated by the nodes are in analogy with earlier embodiments detected in the central unit. The time differences are determined and associated to different data values.

25 Fig. 9 illustrates a block scheme of an embodiment of a central unit 10 according to the present invention driven by alternating voltage. The central unit 10 comprises a voltage source 12, in this embodiment an alternating voltage source. The voltage source 12 supplies power for the operation of the central unit itself as well as to the bus for further transfer to the nodes. The
30 most essential part of the central unit 10 is as above a microcontroller 19. The microcontroller 19 is powered from the voltage source 12 via an AC/DC converter 80. The outputs on the DC side are galvanically separated from the inputs on the AC side, e.g. by means of a transformer included in the AC/DC

converter. The output control signal means 67 in the microcontroller 19 is arranged to provide a signal to a transistor 65A and a transistor 65B. The transistors 65A, 65B are field effect transistors in this embodiment. They have the property that they conduct current in both directions when they are controlled to be in their low impedance state. When they are turned off, their inherent diode conducts current in one direction, but blocks the other. When the control signal makes the transistors 65A and 65B conductive in both directions, these transistors 65A, 65B and the shunt resistor R1 constitute a low impedance connection between the voltage source 12 and the bus over the bus terminals 33 and 34.

The transistors 65A, 65B can also be controlled by the output control signal means 67 to partially block and thereby lower the voltage on the bus. The voltage modulator 14 comprises in this embodiment the transistors 65A, 65B and the output control signal means 67 of the microcontroller 19, for generation of main voltage pulses.

The current that is provided out on the bus passes the shunt resistor R1. By connecting the input terminals 68, 69 of the voltage detecting means 66 in the microcontroller 19 to points on each side of the shunt resistor R1, a voltage drop over the shunt resistor R1 can be measured, which is proportional to the current on the bus. The current detector 16 comprises also in this embodiment the shunt resistor R1 and the voltage detecting means 66 of the microcontroller 19. The voltage detecting means 66 is in this embodiment arranged to be able to detect positive as well as negative pulses. Also in this embodiment, the microcontroller 19 further comprises the means 17 for detecting the time difference associated with the detected current pulses as well as the associating means 18, interpreting the time differences as data.

Inputs 81 and 82 are used by the microcontroller 29 for sensing the voltage from the voltage source 12.

Fig. 10 describes a node 28' intended to be connected to a bus according to the present invention, where the energy is transferred to the nodes and peripheral units in the form of an alternating voltage. The node 28' is connected to a peripheral unit 46 demanding alternating voltage supply, but with moderate stability requirements.

The microcontroller 29 is in this embodiment power supplied from the bus via an AC/DC converter 83. The outputs on the DC side are galvanically separated from the inputs on the AC side, e.g. by means of a transformer included in the AC/DC converter 83. Transistors 70A and 70B, both field effect transistors, are controlled by the output of the output control signal means 78 in analogy with Fig. 9. When these transistors 70A, 70B are controlled to conduct, they will form a low impedance connection between one of the bus terminals 86 of the node 28' and one peripheral unit terminal 88. (Another bus terminal 87 is constantly connected to another peripheral unit terminal 89.) The peripheral unit 46 can thus be operated by this low impedance directly from the alternating current of the bus.

The voltage pulse detector 25 is in this embodiment implemented in the microcontroller 29 and senses the voltage between voltage inputs 84, 85 directly connected to the bus terminals 86, 87. Deviations in voltage derivative as expected from the base alternating voltage indicate the occurrence of a voltage pulse, as discussed above, and time differences between such detected voltage pulses can be determined. In analogy with earlier embodiments, the interpreter 26 interprets the time difference as data.

When the node 28' is going to send data to the central unit, modifications of the current through the peripheral unit 46 are introduced. If the peripheral unit 46 is connected, i.e. if an alternating current flows through the peripheral unit 46, a signal to the transistors 70A, 70B to prohibit the current to flow during a short period of time will give rise to a negative current pulse in the general alternating current curve. If instead the

5 peripheral unit 46 is not connected, i.e. the transistors 70A, 70B are already prohibiting any current to flow, a signal to the transistors 70A, 70B to allow current to flow will give rise to a positive current pulse. (The detector 16 in the central unit 10 is able to detect both types of pulses, see Fig. 9.)

10 One advantage with the present invention is that the use of a pulse position modulation enables a simultaneous data transfer from more than one node to the central unit. Since each transferred data value has its own position, an additional data value will not destroy the first one. In voltage 115 and current 116 curves of Fig. 11 it is illustrated how two nodes send data in the form of current pulses during one and the same main pulse period. A first node sends a data value corresponding to the time difference $t_a - t_1$, while a second node sends a data value corresponding to the time difference $t_b - t_1$. The central unit can detect both pulses 106 and can be arranged to determine the two different time differences. However, the central unit cannot determine from which node the data is sent. The central unit can neither determine if more than one node sends identical data.

20 The possibility for simultaneous sending of data from several nodes can nevertheless easily be used for transmitting e.g. an emergency stop message. If a data frame comprises a number of main pulse periods, one of these periods can be reserved for express messages in the "upbus" direction, i.e. from the nodes to the central unit. A very important message may have a reserved data value, i.e. that particular time separation is not allowed to use for any other express messages in this express message main pulse period. Such a very important message may be unique for a particular node or may be common for a set of nodes. The central unit knows in such a case implicitly from which node or set of nodes the message comes and may immediately take measures accordingly.

25
30
35
40
45
50
55
60
65
70
75
80
85
90
95
100
105
110
115
120
125
130
135
140
145
150
155
160
165
170
175
180
185
190
195
200
205
210
215
220
225
230
235
240
245
250
255
260
265
270
275
280
285
290
295
300
305
310
315
320
325
330
335
340
345
350
355
360
365
370
375
380
385
390
395
400
405
410
415
420
425
430
435
440
445
450
455
460
465
470
475
480
485
490
495
500
505
510
515
520
525
530
535
540
545
550
555
560
565
570
575
580
585
590
595
600
605
610
615
620
625
630
635
640
645
650
655
660
665
670
675
680
685
690
695
700
705
710
715
720
725
730
735
740
745
750
755
760
765
770
775
780
785
790
795
800
805
810
815
820
825
830
835
840
845
850
855
860
865
870
875
880
885
890
895
900
905
910
915
920
925
930
935
940
945
950
955
960
965
970
975
980
985
990
995
1000
1005
1010
1015
1020
1025
1030
1035
1040
1045
1050
1055
1060
1065
1070
1075
1080
1085
1090
1095
1100
1105
1110
1115
1120
1125
1130
1135
1140
1145
1150
1155
1160
1165
1170
1175
1180
1185
1190
1195
1200
1205
1210
1215
1220
1225
1230
1235
1240
1245
1250
1255
1260
1265
1270
1275
1280
1285
1290
1295
1300
1305
1310
1315
1320
1325
1330
1335
1340
1345
1350
1355
1360
1365
1370
1375
1380
1385
1390
1395
1400
1405
1410
1415
1420
1425
1430
1435
1440
1445
1450
1455
1460
1465
1470
1475
1480
1485
1490
1495
1500
1505
1510
1515
1520
1525
1530
1535
1540
1545
1550
1555
1560
1565
1570
1575
1580
1585
1590
1595
1600
1605
1610
1615
1620
1625
1630
1635
1640
1645
1650
1655
1660
1665
1670
1675
1680
1685
1690
1695
1700
1705
1710
1715
1720
1725
1730
1735
1740
1745
1750
1755
1760
1765
1770
1775
1780
1785
1790
1795
1800
1805
1810
1815
1820
1825
1830
1835
1840
1845
1850
1855
1860
1865
1870
1875
1880
1885
1890
1895
1900
1905
1910
1915
1920
1925
1930
1935
1940
1945
1950
1955
1960
1965
1970
1975
1980
1985
1990
1995
2000
2005
2010
2015
2020
2025
2030
2035
2040
2045
2050
2055
2060
2065
2070
2075
2080
2085
2090
2095
2100
2105
2110
2115
2120
2125
2130
2135
2140
2145
2150
2155
2160
2165
2170
2175
2180
2185
2190
2195
2200
2205
2210
2215
2220
2225
2230
2235
2240
2245
2250
2255
2260
2265
2270
2275
2280
2285
2290
2295
2300
2305
2310
2315
2320
2325
2330
2335
2340
2345
2350
2355
2360
2365
2370
2375
2380
2385
2390
2395
2400
2405
2410
2415
2420
2425
2430
2435
2440
2445
2450
2455
2460
2465
2470
2475
2480
2485
2490
2495
2500
2505
2510
2515
2520
2525
2530
2535
2540
2545
2550
2555
2560
2565
2570
2575
2580
2585
2590
2595
2600
2605
2610
2615
2620
2625
2630
2635
2640
2645
2650
2655
2660
2665
2670
2675
2680
2685
2690
2695
2700
2705
2710
2715
2720
2725
2730
2735
2740
2745
2750
2755
2760
2765
2770
2775
2780
2785
2790
2795
2800
2805
2810
2815
2820
2825
2830
2835
2840
2845
2850
2855
2860
2865
2870
2875
2880
2885
2890
2895
2900
2905
2910
2915
2920
2925
2930
2935
2940
2945
2950
2955
2960
2965
2970
2975
2980
2985
2990
2995
3000
3005
3010
3015
3020
3025
3030
3035
3040
3045
3050
3055
3060
3065
3070
3075
3080
3085
3090
3095
3100
3105
3110
3115
3120
3125
3130
3135
3140
3145
3150
3155
3160
3165
3170
3175
3180
3185
3190
3195
3200
3205
3210
3215
3220
3225
3230
3235
3240
3245
3250
3255
3260
3265
3270
3275
3280
3285
3290
3295
3300
3305
3310
3315
3320
3325
3330
3335
3340
3345
3350
3355
3360
3365
3370
3375
3380
3385
3390
3395
3400
3405
3410
3415
3420
3425
3430
3435
3440
3445
3450
3455
3460
3465
3470
3475
3480
3485
3490
3495
3500
3505
3510
3515
3520
3525
3530
3535
3540
3545
3550
3555
3560
3565
3570
3575
3580
3585
3590
3595
3600
3605
3610
3615
3620
3625
3630
3635
3640
3645
3650
3655
3660
3665
3670
3675
3680
3685
3690
3695
3700
3705
3710
3715
3720
3725
3730
3735
3740
3745
3750
3755
3760
3765
3770
3775
3780
3785
3790
3795
3800
3805
3810
3815
3820
3825
3830
3835
3840
3845
3850
3855
3860
3865
3870
3875
3880
3885
3890
3895
3900
3905
3910
3915
3920
3925
3930
3935
3940
3945
3950
3955
3960
3965
3970
3975
3980
3985
3990
3995
4000
4005
4010
4015
4020
4025
4030
4035
4040
4045
4050
4055
4060
4065
4070
4075
4080
4085
4090
4095
4100
4105
4110
4115
4120
4125
4130
4135
4140
4145
4150
4155
4160
4165
4170
4175
4180
4185
4190
4195
4200
4205
4210
4215
4220
4225
4230
4235
4240
4245
4250
4255
4260
4265
4270
4275
4280
4285
4290
4295
4300
4305
4310
4315
4320
4325
4330
4335
4340
4345
4350
4355
4360
4365
4370
4375
4380
4385
4390
4395
4400
4405
4410
4415
4420
4425
4430
4435
4440
4445
4450
4455
4460
4465
4470
4475
4480
4485
4490
4495
4500
4505
4510
4515
4520
4525
4530
4535
4540
4545
4550
4555
4560
4565
4570
4575
4580
4585
4590
4595
4600
4605
4610
4615
4620
4625
4630
4635
4640
4645
4650
4655
4660
4665
4670
4675
4680
4685
4690
4695
4700
4705
4710
4715
4720
4725
4730
4735
4740
4745
4750
4755
4760
4765
4770
4775
4780
4785
4790
4795
4800
4805
4810
4815
4820
4825
4830
4835
4840
4845
4850
4855
4860
4865
4870
4875
4880
4885
4890
4895
4900
4905
4910
4915
4920
4925
4930
4935
4940
4945
4950
4955
4960
4965
4970
4975
4980
4985
4990
4995
5000
5005
5010
5015
5020
5025
5030
5035
5040
5045
5050
5055
5060
5065
5070
5075
5080
5085
5090
5095
5100
5105
5110
5115
5120
5125
5130
5135
5140
5145
5150
5155
5160
5165
5170
5175
5180
5185
5190
5195
5200
5205
5210
5215
5220
5225
5230
5235
5240
5245
5250
5255
5260
5265
5270
5275
5280
5285
5290
5295
5300
5305
5310
5315
5320
5325
5330
5335
5340
5345
5350
5355
5360
5365
5370
5375
5380
5385
5390
5395
5400
5405
5410
5415
5420
5425
5430
5435
5440
5445
5450
5455
5460
5465
5470
5475
5480
5485
5490
5495
5500
5505
5510
5515
5520
5525
5530
5535
5540
5545
5550
5555
5560
5565
5570
5575
5580
5585
5590
5595
5600
5605
5610
5615
5620
5625
5630
5635
5640
5645
5650
5655
5660
5665
5670
5675
5680
5685
5690
5695
5700
5705
5710
5715
5720
5725
5730
5735
5740
5745
5750
5755
5760
5765
5770
5775
5780
5785
5790
5795
5800
5805
5810
5815
5820
5825
5830
5835
5840
5845
5850
5855
5860
5865
5870
5875
5880
5885
5890
5895
5900
5905
5910
5915
5920
5925
5930
5935
5940
5945
5950
5955
5960
5965
5970
5975
5980
5985
5990
5995
6000
6005
6010
6015
6020
6025
6030
6035
6040
6045
6050
6055
6060
6065
6070
6075
6080
6085
6090
6095
6100
6105
6110
6115
6120
6125
6130
6135
6140
6145
6150
6155
6160
6165
6170
6175
6180
6185
6190
6195
6200
6205
6210
6215
6220
6225
6230
6235
6240
6245
6250
6255
6260
6265
6270
6275
6280
6285
6290
6295
6300
6305
6310
6315
6320
6325
6330
6335
6340
6345
6350
6355
6360
6365
6370
6375
6380
6385
6390
6395
6400
6405
6410
6415
6420
6425
6430
6435
6440
6445
6450
6455
6460
6465
6470
6475
6480
6485
6490
6495
6500
6505
6510
6515
6520
6525
6530
6535
6540
6545
6550
6555
6560
6565
6570
6575
6580
6585
6590
6595
6600
6605
6610
6615
6620
6625
6630
6635
6640
6645
6650
6655
6660
6665
6670
6675
6680
6685
6690
6695
6700
6705
6710
6715
6720
6725
6730
6735
6740
6745
6750
6755
6760
6765
6770
6775
6780
6785
6790
6795
6800
6805
6810
6815
6820
6825
6830
6835
6840
6845
6850
6855
6860
6865
6870
6875
6880
6885
6890
6895
6900
6905
6910
6915
6920
6925
6930
6935
6940
6945
6950
6955
6960
6965
6970
6975
6980
6985
6990
6995
7000
7005
7010
7015
7020
7025
7030
7035
7040
7045
7050
7055
7060
7065
7070
7075
7080
7085
7090
7095
7100
7105
7110
7115
7120
7125
7130
7135
7140
7145
7150
7155
7160
7165
7170
7175
7180
7185
7190
7195
7200
7205
7210
7215
7220
7225
7230
7235
7240
7245
7250
7255
7260
7265
7270
7275
7280
7285
7290
7295
7300
7305
7310
7315
7320
7325
7330
7335
7340
7345
7350
7355
7360
7365
7370
7375
7380
7385
7390
7395
7400
7405
7410
7415
7420
7425
7430
7435
7440
7445
7450
7455
7460
7465
7470
7475
7480
7485
7490
7495
7500
7505
7510
7515
7520
7525
7530
7535
7540
7545
7550
7555
7560
7565
7570
7575
7580
7585
7590
7595
7600
7605
7610
7615
7620
7625
7630
7635
7640
7645
7650
7655
7660
7665
7670
7675
7680
7685
7690
7695
7700
7705
7710
7715
7720
7725
7730
7735
7740
7745
7750
7755
7760
7765
7770
7775
7780
7785
7790
7795
7800
7805
7810
7815
7820
7825
7830
7835
7840
7845
7850
7855
7860
7865
7870
7875
7880
7885
7890
7895
7900
7905
7910
7915
7920
7925
7930
7935
7940
7945
7950
7955
7960
7965
7970
7975
7980
7985
7990
7995
8000
8005
8010
8015
8020
8025
8030
8035
8040
8045
8050
8055
8060
8065
8070
8075
8080
8085
8090
8095
8100
8105
8110
8115
8120
8125
8130
8135
8140
8145
8150
8155
8160
8165
8170
8175
8180
8185
8190
8195
8200
8205
8210
8215
8220
8225
8230
8235
8240
8245
8250
8255
8260
8265
8270
8275
8280
8285
8290
8295
8300
8305
8310
8315
8320
8325
8330
8335
8340
8345
8350
8355
8360
8365
8370
8375
8380
8385
8390
8395
8400
8405
8410
8415
8420
8425
8430
8435
8440
8445
8450
8455
8460
8465
8470
8475
8480
8485
8490
8495
8500
8505
8510
8515
8520
8525
8530
8535
8540
8545
8550
8555
8560
8565
8570
8575
8580
8585
8590
8595
8600
8605
8610
8615
8620
8625
8630
8635
8640
8645
8650
8655
8660
8665
8670
8675
8680
8685
8690
8695
8700
8705
8710
8715
8720
8725
8730
8735
8740
8745
8750
8755
8760
8765
8770
8775
8780
8785
8790
8795
8800
8805
8810
8815
8820
8825
8830
8835
8840
8845
8850
8855
8860
8865
8870
8875
8880
8885
8890
8895
8900
8905
8910
8915
8920
8925
8930
8935
8940
8945
8950
8955
8960
8965
8970
8975
8980
8985
8990
8995
9000
9005
9010
9015
9020
9025
9030
9035
9040
9045
9050
9055
9060
9065
9070
9075
9080
9085
9090
9095
9100
9105
9110
9115
9120
9125
9130
9135
9140
9145
9150
9155
9160
9165
9170
9175
9180
9185
9190
9195
9200
9205
9210
9215
9220
9225
9230
9235
9240
9245
9250
9255
9260
9265
9270
9275
9280
9285
9290
9295
9300
9305
9310
9315
9320
9325
9330
9335
9340
9345
9350
9355
9360
9365
9370
9375
9380
9385
9390
9395
9400
9405
9410
9415
9420
9425
9430
9435
9440
9445
9450
9455
9460
9465
9470
9475
9480
9485
9490
9495
9500
9505
9510
9515
9520
9525
9530
9535
9540
9545
9550
9555
9560
9565
9570
9575
9580
9585
9590
9595
9600
9605
9610
9615
9620
9625
9630
9635
9640
9645
9650
9655
9660
9665
9670
9675
9680
9685
9690
9695
9700
9705
9710
9715
9720
9725
9730
9735
9740
9745
9750
9755
9760
9

node address. The data value will in such a case implicitly comprise not only the message content, but also the node address. As an example, if a system comprises 4 nodes and each node may send a "0", a "1" or a "2", indicating e.g. three different status codes of operation of the associated peripheral units, 12 different data values can represent each combination of node and status code. The central unit can then by the data value itself determine from which node the data is sent and what the corresponding status is. In such a scheme, there will be no risk for two nodes to send an identical data value.

One aspect of the ability of sending simultaneous data from several nodes is the possibility for implementing a more extended express message function. Express messages are node messages that require fast reactions from the system and where normal node monitoring routines are insufficiently fast.

If a node needs to leave an express message, the central unit has to be made aware of this need. The node has thus to send a request for sending a longer or more information-rich message and also inform the central unit about which node is asking. When such a request is received, the central unit may issue a message to the (or several) concerned node(s) to allow for the actual message to be sent. One possibility to provide this is to reserve certain main pulse periods for transmission of such attention requests. Since most frames typically comprises at least one data unit related to an address of a receiving node or group of nodes, the corresponding main pulse period is difficult to use for normal data communication from a node to the central units, simply due to the fact that the nodes do not yet know which node is addressed. Such an addressing main pulse period may then in the "upbus" direction be use for express message requests. The central unit detects the express message request and may even in the successive frame address the node that put the request to allow for the actual express message to be sent. The response time for an express message can thereby be shortened considerably.

An example may illustrate this possibility more in detail. Let us assume that a model system comprises 64 indicators, controlled by the system, and 64 switches that control one of the indicators each. The switches are connected to one node each. When a switch is closed, a corresponding indicator somewhere else in the system should be activated or deactivated. The time from the closing of the switch to the activation of the indicator is called response time. In the model system, there is a request that the response time should not exceed 100 ms.

In a conventional system of this kind, the central unit typically addresses the nodes one at a time in a predetermined order. One node at a time is read to see if its switch has been closed (or opened). In this example, it takes 10 ms to address and read a node and its switch. The scanning of all 64 switches takes $64 \times 10 \text{ ms} = 640 \text{ ms}$. This sequential scanning of nodes in the system is repeated periodically. When a switch is closed, it may in the worst case take 640 ms before the central unit discovers it. The response time may thereby be as high as 640 ms. Such response time increases in proportion to the number of nodes. The system can thus only manage to monitor a limited number of nodes before the response time becomes unreasonably long. The response time thus limits the ability of the system to handle many nodes with a short response time.

According to the present invention, a procedure with express messages can be designed. In Fig. 12, a schematic description of a number of frames in a communication system according to the present invention is illustrated. In this example, every frame consists of 7 main pulse periods. Every main pulse period (except the calibration period) can assume 16 different lengths, which means that it can transfer 16 different values, i.e. information corresponding to 4 binary data bits. Each frame can thereby transfer 6×4 data bits, since the calibration period is not used. During each main pulse period, all nodes are allowed to send a current pulse on the bus corresponding to one out of 16 different time distances from the initial main pulse. This means that

every main pulse period may transfer 4 binary data bits from a node to the central unit.

5 According to Fig. 12, every frame has been formatted in such a way that the central unit sends an address consisting of 2 data units corresponding to each 4 binary data bits and additional data consisting of 4 data units of each 4 binary data bits. Simultaneously, the nodes can send information to the central unit. The first two main pulse periods can be used for express message requests according to the present embodiment. The next four main pulse periods may be used by the addressed node to send back information to the central unit. The last main pulse period, corresponding to the calibration period, can be used for transferring checksums.

15 The express message periods are reserved for simultaneous sending of current pulses from several of the nodes. Normally, if nothing has happened, no data at all is sent from the nodes during the express message periods. If a switch of a node is closed, this node will generate a current pulse in the next frame to request an express message procedure. If the number of nodes is small enough, the node can simply send a representation of its address. 20 Since the address is unique for each node, the central unit knows immediately which node is calling. In the present example 16 addresses can be represented in the first express message period and 16 in the second one, which means that 32 nodes can be identified immediately. However, in the present embodiment, 64 nodes are present, which means that a somewhat more complicated procedure has to be employed.

25 The 64 nodes of the present example are divided into 8 node groups with 8 nodes in each. If a switch of the 6th node in node group 5 is closed during time of the first data frame, this node will generate a current pulse in the next frame (frame 2). The current pulse will have a time difference that corresponds to the data value 5. The central unit detects this data value and in the successive data frame, frame 3, the central unit addresses collectively all nodes of node group 5 with the question "who is asking for an express 30

message?". The node in question will respond to such a message by already in the same frame reply with a new current pulse, now in main pulse period 3. The time position of the current pulse corresponds to the data value 6, i.e. the 6th node of group 5. The central unit senses this data value and may already in the successive frame, frame 4, send an instruction to the node handling indicator 56 to turn it on. The response time thus becomes around 3 frames long, in the very worst case, almost 4 frames. However, if frame time was 10 ms, a response time never exceeds 40 ms, remarkably shorter than for conventional systems.

10

Also, even if the number of nodes to be monitored increases somewhat, the total response time will not increase. If each pulse corresponds to 4 binary bits and two main pulse periods are available for express messages, such a two-step procedure described above will be able to handle $2 \cdot 16 \cdot 16 = 512$ nodes without increasing the response time.

15

Also if more than one switch is closed during one and the same frame period, this is easy to handle according to the present invention, due to the possibility of simultaneous transferring of data from different nodes. During frame 3, the switches of the 3rd and 7th node of node group 6 were closed. In frame 4, both these nodes generates a current pulse in the second main pulse period corresponding to a value of 6. The central unit detects the value of 6, but does not know that there are two switches closed, since no measure of the pulse amplitude is made. In analogy with the previous example, the central unit addresses all nodes of group 6 in the following frame (frame 5). Both node 3 and 7 will respond to this inquiry and generate one current pulse each in main pulse period 3 of frame 5. The central unit now detects two current pulses and realises that two switches are closed. In the two successive frames, frame 6 and 7, respectively, the corresponding indicators are order to be activated.

20

25

30

As another example, during frame 6, switches of the 2nd node of node group 4 and the 1st node of node group 5 are closed. In frame 7, both these nodes

Huvudfoxen

generate current pulses, but now at different times. The central unit detects two pulses corresponding to the values of 4 and 5, respectively. In frame 8, an inquiry to node group 4 is sent, whereby the 2nd node replies. In frame 9, the corresponding indicator is controlled to be activated. In frame 10, an inquiry to node group 5 is sent, whereby the 1st node replies. Finally, in frame 11, the corresponding indicator is controlled to be activated.

Anyone skilled in the art understands that more than two simultaneous node messages are possible to detect by the principles described above.

In Fig. 13, a flow diagram illustrating an embodiment of a procedure according to the present invention is shown. The procedure starts in step 200. In step 202, a voltage is provided between the conductors in a bus connecting a central unit and a number of nodes. In step 204, voltage pulses are modulated onto the bus by the central unit. The time difference between successive voltage pulses takes one of n distinct predetermined values, where $n > 2$. The modulated voltage pulses are detected in the nodes in step 206, whereupon time separations of the detected pulses are determined in step 208 and associated in step 210 to a corresponding data quantity. Steps 204-210 correspond to a data transfer from the central unit to the nodes.

In step 212, current pulses are created by at least one node on the bus, representing data intended for the central unit. The time difference between successive voltage pulses takes one of k distinct predetermined values, where $k > 2$. The time difference between such a current pulse and the closes previous voltage pulse is determined by the central unit in step 214, and in step 216 such a time separation is associated with a data quantity. Steps 212-216 correspond to a data transfer from the nodes to the central unit. The procedure is ending in step 218.

The above flow diagram should not be interpreted in a strictly sequential manner. The step 202 and the step groups 204-210 and 212-216 should

instead be understood as essentially independent and simultaneous part procedures.

5

It will be understood by those skilled in the art that various modifications and changes may be made to the present invention without departure from the scope thereof, which is defined by the appended claims. It will also be understood by those skilled in the art that various combinations of embodiments described above are favourable to implement.

1
2
3
4
5
6
7
8
9
10

CLAIMS

1. Electrical system (1) comprising:

a central unit (10);

at least one node (20-24; 28; 28'); and

bus arrangement (30) connecting the at least one node (20-24; 28; 28') and the central unit (10) for transfer of data there between;

the bus arrangement (30) having a single conductor pair (31, 32);

the central unit (10) comprising a voltage supply (12) arranged to provide a voltage between the conductors (31, 32) in the conductor pair;

the central unit (10) further comprising a voltage modulator (14), arranged to modulate voltage pulses onto the conductor pair (31, 32) representing data to be transferred from the central unit (10) to at least one of the number of nodes (20-24; 28; 28');

the at least one of the number of nodes (20-24; 28; 28') comprising a detector (25) of the modulated voltage pulses or quantities directly related thereto;

the at least one of the number of nodes (20-24; 28; 28') further comprising an interpreter (26), interpreting the detected modulated voltage pulses as transferred data

characterised in that

the modulator (14) is arranged to creating at least two successive voltage pulses (60, 61; 102);

whereby a time separation ($\Delta t_1 - \Delta t_7$; $\Delta t_9 - \Delta t_{12}$) between the successive voltage pulses (60, 61; 102) takes one of n distinct predetermined first values, where $n > 2$, each of the n distinct predetermined values corresponding to a predetermined data quantity; and

the interpreter (26) in turn comprises means for determining the time separation ($\Delta t_1 - \Delta t_7$; $\Delta t_9 - \Delta t_{12}$) between the successive voltage pulses (60, 61; 102) and means for associating the determined time separation ($\Delta t_1 - \Delta t_7$; $\Delta t_9 - \Delta t_{12}$) with a corresponding data quantity.

2. Electrical system according to claim 1, **characterised in that** the at least one of the number of nodes (20-24; 28; 28') further comprises:

means (27) for creating a current pulse (64; 106) on the conductor pair (31, 32) representing data to be transferred from the at least one of the number of nodes (20-24; 28; 28') to the central unit (10);

whereby a time separation (Δt_8 ; $\Delta t_{13}-\Delta t_{16}$) between the current pulse (64; 106) and the closest preceding voltage pulse (60; 102) takes one of k distinct predetermined values, where $k > 2$, each of the k distinct predetermined values corresponding to a predetermined data quantity; and the central unit (10) further comprises:

detector (16) for the current pulses;

means (17) for determining the time separation (Δt_8 ; $\Delta t_{13}-\Delta t_{16}$) between the current pulse (64; 106) and the closest preceding voltage pulse (60; 102); and

means (18) for associating, in the central unit (10), the determined time separation (Δt_8 ; $\Delta t_{13}-\Delta t_{16}$) between the current pulse (64; 106) and the closest preceding voltage pulse (60; 102) with a corresponding data quantity.

3. Electrical system according to claim 2, **characterised in that** more than one node (20-24; 28; 28') is arranged to send data to the central unit (10) within the same time period between two successive voltage pulses (60, 61; 102).

4. Electrical system according to any of the claims 1 to 3, **characterised in that** the at least one of the number of nodes (20-24; 28; 28') further comprises means for extracting electrical power from the voltage between the conductor pair (31, 32).

5. Electrical system according to claim 4, **characterised by** a peripheral unit (46) associated with the at least one of the number of nodes (20-24; 28; 28'), said peripheral unit (46) being connected directly between the conductor pair (31, 32) via only switching means (72; 70A, 70B).

6. Method of communication in an electrical system (1) having a central unit (10) connected to a number of nodes (20-24; 28; 28') by a common bus arrangement (30) with a single conductor pair (31, 32), comprising the steps of:

5 providing a voltage between the conductors (31, 32) in the conductor pair;

modulating, in the central unit (10), voltage pulses (60, 61; 102) on the conductor pair representing data to be transferred from the central unit (10) to at least one of the number of nodes (20-24; 28; 28');

10 detecting the modulated voltage pulses (60, 61; 102) or quantities directly related thereto in the at least one of the number of nodes (20-24; 28; 28'); and

interpreting, in the at least one of the number of nodes (20-24; 28; 28'), the detected modulated voltage pulses (60, 61; 102) as transferred data,

15 **characterised in that**

the step of modulating in turn comprises the step of creating at least two successive voltage pulses (60, 61; 102);

whereby a time separation ($\Delta t_1 - \Delta t_7$; $\Delta t_9 - \Delta t_{12}$) between the successive voltage pulses (60, 61; 102) takes one of n distinct predetermined first values, where $n > 2$, each of the n distinct predetermined values corresponding to a predetermined data quantity;

20 the interpreting step in turn comprises the steps of:

determining the time separation ($\Delta t_1 - \Delta t_7$; $\Delta t_9 - \Delta t_{12}$); and

25 associating the determined time separation ($\Delta t_1 - \Delta t_7$; $\Delta t_9 - \Delta t_{12}$) with a corresponding data quantity.

7. Method according to claim 6, **characterised by** the further steps of:

creating, in the at least one of the number of nodes (20-24; 28; 28'), a current pulse (64; 106) on the conductor pair (31, 32) representing data to be transferred from at least one of the number of nodes (20-24; 28; 28') to the central unit (10);

30 whereby a time separation (Δt_8 ; $\Delta t_{13} - \Delta t_{16}$) between the current pulse (64; 106) and the closest preceding voltage pulse (60; 102) takes one of k

distinct predetermined values, where $k > 2$, each of the k distinct predetermined values corresponding to a predetermined data quantity;

detecting the current pulses (64; 106) in the central unit (10);

determining, in the central unit (10), the time separation (Δt_8 ; Δt_{13} - Δt_{16}) between the current pulse (64; 106) and the closest preceding voltage pulse (60; 102); and

associating, in the central unit (10), the determined time separation (Δt_8 ; Δt_{13} - Δt_{16}) between the current pulse (64; 106) and the closest preceding voltage pulse (60; 102) with a corresponding data quantity.

8. Method according to claim 7, **characterised in that** more than one node (20-24; 28; 28') sends data to the central unit (10) within the same time period between two successive voltage pulses (60, 61; 102).

9. Method according to any of the claims 6 to 8, **characterised by** the further step of supplying electrical power to the number of nodes (20-24; 28; 28') from the voltage between the conductor pair (31, 32).

10. Method according to any of the claims 6 to 9, **characterised by** sending calibration data from the central unit (10) to the nodes (20-24; 28; 28') as two voltage pulses having a time separation being distinct in relation to time separations representing other data than calibration data.

11. Method according to claim 10, **characterised in that** said time separation representing said calibration data is larger than time separations representing other data than calibration data.

12. Method according to claim 10 or 11, **characterised in that** said time separation representing said calibration data is situated within a predetermined range.

13. Method according to any of the claims 10 to 12, **characterised by** calibrating a node time reference of at least one of the number of nodes (20-

24; 28; 28') based on a measured value of the voltage pulse time separation (Δt_5 ; Δt_7 ; Δt_{12}) of said calibration data.

14. Method according to any of the claims 10 to 13, **characterised in that** the data to be transferred is sent in data frames, whereby the method comprises the further step of synchronizing the start of each data frame to the m th voltage pulse following a calibration data period.

15. Method according to claim 14, **characterised in that** a time separation between the start of two successive data frames is equal to a predetermined synchronizing value, whereby the method comprises the further steps of calibrating node time reference of at least one of the number of nodes (20-24; 28; 28') based on a measured value of the time separation between the start of two successive data frames and additionally based on the predetermined synchronizing value.

16. Method according to any of the claims 7 or 8 or to any of the claims 9 to 15 when in turn being directly or indirectly dependent on claim 7, **characterised in that** the data to be transferred is sent in data frames, in which at least one data position of data transferred from at least one of the number of nodes (20-24; 28; 28') to the central unit (10) is assigned as an express data position, whereby at least one of the number of nodes (20-24; 28; 28') sends data associated with an express message in the express data position.

17. Method according to claim 16, **characterised in that** at least two of the number of nodes (20-24; 28; 28') send data associated with an express message in the same express data position.

18. Method according to claim 16 or 17, **characterised in that** said data associated with an express message comprises an identification of the node (20-24; 28; 28') sending said data associated with an express message.

19. Electric signal for data communication, comprising voltage pulses (60, 61; 102) modulated on a main voltage, **characterised by** at least two successive voltage pulses (60, 61; 102), whereby a time separation ($\Delta t_1 - \Delta t_7$; $\Delta t_9 - \Delta t_{12}$) between the successive voltage pulses (60, 61; 102) takes one of n distinct predetermined first values, where $n > 2$, each of the n distinct predetermined values corresponding to a predetermined data quantity.

20. Electric signal according to claim 19, **characterised by** at least one current pulse (64; 106), whereby a time separation (Δt_8 ; $\Delta t_{13} - \Delta t_{16}$) between the current pulse (64; 106) and the closest preceding voltage pulse (60; 102) takes one of k distinct predetermined values, where $k > 2$, each of the k distinct predetermined values corresponding to a predetermined data quantity.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100

ABSTRACT

5 Data communication in an electrical system uses the time difference between two successive current or voltage pulses to represent different data values. The time differences ($\Delta t_9 - \Delta t_{16}$) can assume more than two different predetermined values, and thereby each pulse can represent more than one data bit. A central unit transfers data to a number of nodes by modulating voltage pulses onto a base voltage supplying power to the nodes. The time difference ($\Delta t_9 - \Delta t_{12}$) between successive voltage pulses represents a data value. The nodes transfer data back to the central unit using current pulses, whereby the time difference ($\Delta t_{13} - \Delta t_{16}$) between the latest voltage pulse and the current pulse represents the data sent to the central unit. Data from two or more nodes are possible to transfer simultaneously without disturbing each other. The base voltage on the bus can be AC or DC.

10

15

(Fig. 8)




Fig. 1

2/9




Fig. 2




Fig. 3

3/9




Fig. 4




Fig. 5

4/9




Fig. 6




Fig. 7

5/9






Fig. 8

00011319



Ink. t. Patent- och reg.verket

2003-04-14

Huvudfaxen Kassar

7/9




Fig. 11

00011311-9

8/9

MAIN PULSE PERIOD

1	2	3	4	5	6	7
---	---	---	---	---	---	---

FRAME 1

FROM CENTRAL UNIT
FROM NODES

ADDR	ADDR	DATA	DATA	DATA	DATA	CAL
EXPR	EXPR	DATA	DATA	DATA	DATA	CHCK

FRAME 2

FROM CENTRAL UNIT
FROM NODES

	5					

FRAME 3

FROM CENTRAL UNIT
FROM NODES

GRP	5					
		6				

FRAME 4

FROM CENTRAL UNIT
FROM NODES

IND	56	1				
	6					

FRAME 5

FROM CENTRAL UNIT
FROM NODES

GRP	6					
		3 & 7				

FRAME 6

FROM CENTRAL UNIT
FROM NODES

IND	63	1				

FRAME 7

FROM CENTRAL UNIT
FROM NODES

IND	67	1				
	4 & 5					

FRAME 8

FROM CENTRAL UNIT
FROM NODES

GRP	4					
		2				

FRAME 9

FROM CENTRAL UNIT
FROM NODES

IND	42	1				

FRAME 10

FROM CENTRAL UNIT
FROM NODES

GRP	5					
		1				

FRAME 11

FROM CENTRAL UNIT
FROM NODES

IND	51	1				

Fig. 12

9/9




Fig. 13

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ BLACK BORDERS
- ☐ IMAGE CUT OFF AT TOP, BOTTOM OR SIDES
- ☐ FADED TEXT OR DRAWING
- ☐ BLURRED OR ILLEGIBLE TEXT OR DRAWING
- ☐ SKEWED/SLANTED IMAGES
- ☐ COLOR OR BLACK AND WHITE PHOTOGRAPHS
- ☐ GRAY SCALE DOCUMENTS
- ☒ LINES OR MARKS ON ORIGINAL DOCUMENT
- ☐ REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY
- ☐ OTHER: _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.